



The MMP, including installed Magnum products are covered under a new, five-year warranty!



The MMP Enclosure



The MMP shown with inverter (sold separately) and optional remote and backplate.

The MMP – Mini Magnum Panel is an inclusive, easy-to-install panel designed to work with one Magnum MS-AE, MS-PAE, MS, RD or other non-Magnum inverter / charger.

#### FEATURES:

- **Small footprint:** only 12.5" wide x 18" tall x 8" deep
- **Money-saving design:** not only is the MMP less expensive, but it is pre-wired for fast installation, saving labor costs
- **Easy access:** front-mounted breakers and remote (optional)
- **Choices:** can be wired for 120 VAC or 120/240 VAC output
- **Inclusive:** works with non-Magnum inverter / chargers (stand-alone parts included)
- **Listed:** ETL listed to UL1741 and CSA C22.2 107-01
- **DC load breakers:** fits either din rail or back-mount DC load breakers.

#### INCLUDES:

- One DC breaker – 175A or 250A
- One AC bypass breaker – 30A dual pole or 60A single pole
- One AC input breaker – 30A dual pole or 60A single pole
- 500A/50mv DC shunt
- DC buss bars for battery positive and negative
- Din rail or back mount for optional DC mini breakers – will hold up to eight breakers
- Inverter hood

| Part Numbers | Dimensions (h x w x d)                      | Shipping Weight |
|--------------|---|-----------------|
| MMP250-30D   | 22" x 15" x 13" (55.9 cm x 38.1 cm x 33 cm) | 32 lb (14.5 kg) |
| MMP250-60S   | 22" x 15" x 13" (55.9 cm x 38.1 cm x 33 cm) | 31 lb (14.1 kg) |
| MMP175-30D   | 22" x 15" x 13" (55.9 cm x 38.1 cm x 33 cm) | 32 lb (14.5 kg) |
| MMP175-60S   | 22" x 15" x 13" (55.9 cm x 38.1 cm x 33 cm) | 31 lb (14.1 kg) |